


IP Recorder

NVR-6408-H1/F



KEY FEATURES



•Video and audio channels: 8 •Supported protocols: ONVIF, RTSP

•Supported protocols: OWVF, RTSP •Recording speed up to 240 fps at 3840 x 2160 •Supports resolution up to 3840 x 2160 •Recorded stream size: 80 Mb/s in total from all cameras

Internal HDDs mount: 1

•Monitor outputs: 2 (HDMI, VGA)

Face recognition

DIMENSIONS



| IP Cameras | up to 8 channels at 3840 x 2160 resolution (video + audio) |
|---------------------------------|---|
| Compression | H.264, H.264+, H.265 |
| Monitor Output | main (split screen, full screen, sequence): 1 x VGA, 1 x HDMI (4K UltraHD) (up to 2 monitors simultaneously) |
| Dualstreaming Support | yes |
| Fisheye Support | yes, 3000/6000 IP series cameras |
| AUDIO | |
| Audio Input/Output | 1 x line-in (RCA) / 1 x HDMI, 1 x line-out (RCA) |
| RECORDING | |
| Stream Size | 80 Mb/s in total from all cameras |
| Recording Mode | time-lapse, triggered by: manual, alarm input, motion detection, intelligent image analysis functions |
| Prealarm/Postalarm | up to 5 s/up to 600 s |
| DISPLAY | |
| Display Speed | 240 fps (8 x 30 fps) |
| PLAYBACK | |
| Playback Speed | 240 fps (8 x 30 fps) |
| Recorded Data Search | by date/time, events, motion in a defined area, related to face recognition |
| BACKUP | |
| Backup Methods | USB port (HDD or Flash memory), network |
| Backup File Format | AVI, RPAS (player included) |
| STORAGE | |
| Internal Storage | available mount: 1 x HDD 3.5" 10 TB SATA |
| Total Internal Capacity | 10 TB |
| ALARM | |
| Internal Alarm Input/Output | 8/4 relay type |
| Camera Alarm Input/Output | supports IP camera's alarm input/output |
| Motion Detection | supports camera's motion detection |
| System Reaction to Alarm Events | buzzer, alarm output activation, recording activation, PTZ, e-mail w |

NoVus'

INTELLIGENT IMAGE ANALYSIS





IP Recorder NVR-6408-H1/F

| Supported Functions | Exception, Scene Change, Video Blurred, Video Color Cast, Tripwire, Zone entrance, Abandoned Object, Object Disappearance, Face Detection, Face Recognition, Perimeter Intrusion Detection by pedestrian or vehicle, Line Cross Detection by pedestrian or vehicle, Analysis of Recognized Number Plate Numbers (LPR) |
|-----------------------------------|---|
| NETWORK | |
| Network Interface | 1 x Ethernet - RJ-45 interface, 10/100/1000 Mbit/s |
| Network Protocols Support | HTTP, TCP/IP, IPv4/v6, FTP, DHCP, DNS, DDNS, NTP, RTSP, UPnP, SNMP, SMTP, P2P, HTML5 |
| ONVIF Protocol Support | Profile S (ONVIF 2.2 or higher) |
| PC/MAC Software | NMS, Internet Explorer, Firefox, Chrome, Opera, Safari, N Control 6000, Edge/Safari, N Control 6000 |
| Mobile applications | SuperLive Plus (iPhone, Android) |
| Number of Simultaneous Connection | nsup to 5 clients, up to 12 main streams or 32 substreams or 8 playback streams in total |
| Bandwidth | 80 Mb/s in total to all client workstations |
| PTZ | |
| PTZ Functions | pan/tilt/zoom, preset commands |
| AUXILIARY INTERFACES | |
| USB Ports | 1 x USB 2.0, 1 x USB 3.0 |
| OPERATING SYSTEM | |
| Operating System | Linux |
| Operation Mode | triplex |
| OSD | languages: Polish, English, others |
| Control | PC mouse (in-set included), network |
| System Diagnostic | automatic control of: HDDs, network, camera connection loss |
| Security | password protection, IP filtering, MAC filtering |
| INSTALLATION PARAMETERS | |
| Dimensions (mm) | 300 (W) x 44 (H) x 248 (D) |
| Weight | 0.65 kg (without HDD) |
| Power Supply | 12 VDC (100 ~ 240 VAC/12 VDC PSU in-set included) |
| Power Consumption | 18 W (with 1 HDD) |

 Power Consumption
 18 W (with 1 HDD)

 Operating Temperature
 -10°C ~ 50°C

In order to take full advantage of the recorder capabilities it is recommended to use NOVUS IP 6000 series cameras.

The availability of individual functions (including face recognition) depends on the model of cameras used as well as the software version of the recorder and cameras.

In order to create face recognition system please deploy 6000 series cameras with "F" in the model name only.

Detailed data on camera compatibility with recorders and compatible hard drives can be found in the compatibility tables available in the DOWNLOADABLE FILES tab.

